



UNIVERSITY
OF WOLLONGONG
AUSTRALIA

University of Wollongong
Research Online

University of Wollongong Thesis Collection
1954-2016

University of Wollongong Thesis Collections

2010

Enhanced performance of delayed teleoperator systems operating within nondeterministic environments

Laurence Bate

University of Wollongong, lbate@uow.edu.au

UNIVERSITY OF WOLLONGONG

COPYRIGHT WARNING

You may print or download ONE copy of this document for the purpose of your own research or study. The University does not authorise you to copy, communicate or otherwise make available electronically to any other person any copyright material contained on this site. You are reminded of the following:

This work is copyright. Apart from any use permitted under the Copyright Act 1968, no part of this work may be reproduced by any process, nor may any other exclusive right be exercised, without the permission of the author.

Copyright owners are entitled to take legal action against persons who infringe their copyright. A reproduction of material that is protected by copyright may be a copyright infringement. A court may impose penalties and award damages in relation to offences and infringements relating to copyright material. Higher penalties may apply, and higher damages may be awarded, for offences and infringements involving the conversion of material into digital or electronic form.

Recommended Citation

Bate, Laurence, Enhanced performance of delayed teleoperator systems operating within nondeterministic environments, Doctor of Philosophy thesis, University of Wollongong. School of Electrical, Computer and Telecommunications Engineering, University of Wollongong, 2010. <http://ro.uow.edu.au/theses/3163>

Research Online is the open access institutional repository for the University of Wollongong. For further information contact the UOW Library: research-pubs@uow.edu.au

NOTE

This online version of the thesis may have different page formatting and pagination from the paper copy held in the University of Wollongong Library.

UNIVERSITY OF WOLLONGONG

COPYRIGHT WARNING

You may print or download ONE copy of this document for the purpose of your own research or study. The University does not authorise you to copy, communicate or otherwise make available electronically to any other person any copyright material contained on this site. You are reminded of the following:

Copyright owners are entitled to take legal action against persons who infringe their copyright. A reproduction of material that is protected by copyright may be a copyright infringement. A court may impose penalties and award damages in relation to offences and infringements relating to copyright material. Higher penalties may apply, and higher damages may be awarded, for offences and infringements involving the conversion of material into digital or electronic form.

**ENHANCED PERFORMANCE OF DELAYED TELEOPERATOR
SYSTEMS OPERATING WITHIN NONDETERMINISTIC
ENVIRONMENTS**

A thesis submitted in fulfilment of the requirements for the award of the degree

DOCTOR OF PHILOSOPHY

from

UNIVERSITY OF WOLLONGONG

by

LAURENCE BATE

BACHELOR OF ENGINEERING (ELECTRICAL)

SCHOOL OF ELECTRICAL, COMPUTER AND TELECOMMUNICATIONS
ENGINEERING

2010

THESIS CERTIFICATION

I, Laurence Bate, declare that this thesis submitted in fulfilment of the requirements for the award of a Doctor of Philosophy in the School of Electrical, Computer and Telecommunications Engineering, University of Wollongong, is wholly my own work unless otherwise referenced or acknowledged. The document has not been submitted for qualification at any other academic institution.

Laurence Bate

30th January 2010

ABSTRACT

Bilateral force feedback teleoperation provides the operator with an enhanced real-time understanding of the remote slave environment. It is common for an uncompensated delay within a closed loop path to lead to system instability.

The control problem becomes significantly more complex when the delay conditions are not foreseeable. A good example of such conditions is when the feedback control loop includes the internet, as in remotely controlled teleoperators. Closed loop bilateral teleoperation via a communications path which has no clearly defined or predictable delay time presents difficulty in maintaining both robust stability and adequate system performance for all delay conditions.

In light of this researchers have developed a new transmission line based control law through the introduction of the 'Wave Variable' to enable stable teleoperator systems in the presence of network delays. However wave variables, by their inherent scattering design introduce reflections at the wave junctions. These reflections can prove very disorientating for the operator of a wave based teleoperator.

In this research the existing wave variable teleoperator architecture is augmented to establish stable robust bilateral teleoperator operation which minimizes the return wave based reflections, thus facilitating good teleoperator performance characteristics to allow operation in nonlinear environments.

The work presented in this thesis results in a new teleoperator architecture which: 1) improves wave based teleoperator transient response for the tasks of position tracking and contact stability without the need for prior knowledge of the remote environment wave reflections; 2) enhances force feedback fidelity, with particular focus on the ability to use the teleoperator in complex nonlinear environments such as stick-slip friction; 3) guarantees stable operation of the teleoperation without prior knowledge of the communications delay.

The new delayed bilateral teleoperator architecture is tested by simulations, and experimentally and comprehensively verified on two different teleoperator systems. One of these is a bilateral single degree of freedom teleoperator which consists of Master and Slave manipulators of identical characteristics; the other test bed consists of a Slave manipulator built specifically for non linear stick-slip control experiments.

ACKNOWLEDGEMENTS

I would like to take this opportunity to express my gratitude to the people around me who have helped me through the challenging times I have undergone during these last few years in order to make my work become a finished product; in particular my supervisor: Professor Chris Cook and my co-supervisor Dr. Zheng Li.

TABLE OF CONTENTS

THESIS CERTIFICATION.....	I
ABSTRACT	II
ACKNOWLEDGEMENTS.....	IV
TABLE OF CONTENTS.....	5
LIST OF FIGURES	9
LIST OF TABLES	13
CHAPTER 1 : INTRODUCTION.....	1
1.1 BACKGROUND	1
1.2 THESIS GOALS	4
1.3 OUTLINE OF THE THESIS.....	5
CHAPTER 2 : TELEOPERATION REVIEW.....	7
2.1 INTRODUCTION	7
2.2 BILATERAL TELEOPERATOR REPRESENTATION	13
2.3 DELAYED TELEOPERATION	16
2.4 WAVE TELEOPERATION.....	18
2.5 WAVE TELEOPERATION REFLECTIONS.....	24
2.6 IMPEDANCE MATCHING ARCHITECTURES.....	28
2.6.1 <i>Impedance Matched Teleoperator At Slave and Master Using Matching Elements</i>	<i>28</i>
2.6.2 <i>Impedance Matched Teleoperator At Slave Only</i>	<i>31</i>
2.6.3 <i>Adaptive Impedance Matching</i>	<i>33</i>
2.6.4 <i>Reflection Cancellation By Prediction Modelling</i>	<i>35</i>
2.7 TELEOPERATION OVER THE INTERNET	40
2.8 DISCUSSION AND SUMMARY OF THE LITERATURE REVIEW	42
CHAPTER 3 : MODIFIED VERSION OF THE WAVE EQUATION	48
3.1 INTRODUCTION	48
3.2 DERIVATION OF TELEGRAPHER'S EQUATIONS	48
3.3 WAVE VARIABLE DERIVATION	51
3.4 WAVE REFLECTION CANCELLATION WITHIN THE WAVE VARIABLE DOMAIN.....	55
3.5 STABILITY ANALYSIS OF THE NEW TELEOPERATOR ARCHITECTURE.....	61

3.5.1	<i>Stability Analysis Using The Scattering Operator</i>	61
3.5.2	<i>Stability Analysis Using Power Flow</i>	64
3.5.3	<i>Stability Analysis For Asymmetric Communications Delays</i>	65
3.5.4	<i>Stability Analysis For Asymmetric Time Varying Communications Delays</i>	67
3.6	CONCLUSIONS.....	72
CHAPTER 4 : EXPERIMENTAL EQUIPMENT.....		74
4.1	INTRODUCTION	74
4.2	TELEOPERATOR TEST BED	74
4.3	CONTROL INTERFACE AND DIGITAL SIGNAL PROCESSING.....	76
4.4	CONTROL SCHEME.....	79
4.5	ELECTRICAL CIRCUIT RESPONSE.....	80
4.6	MECHANICAL SYSTEM PARAMETERS.....	80
4.7	TEST BED WITH NON-LINEAR STICK SLIP LOAD.....	83
4.8	STICK SLIP TEST BED — ELECTRICAL CIRCUIT RESPONSE	86
4.9	STICK SLIP TEST BED — MECHANICAL SYSTEM PARAMETERS	86
4.10	TRANSMISSION DELAY	88
4.11	CONCLUSIONS.....	89
CHAPTER 5 : MODELLING AND SIMULATION.....		91
5.1	INTRODUCTION	91
5.2	SYSTEM MODELLING.....	91
5.3	MODELLING OF THE TELEOPERATOR TEST BED	92
5.4	MODELLING OF THE SLAVE ENVIRONMENT.....	93
5.4.1	<i>Contact with a solid wall</i>	93
5.4.2	<i>Non linear Stick Slip Environment</i>	94
5.5	SIMULATION RESULTS.....	97
5.5.1	<i>Original Wave Variable Teleoperator Architecture</i>	98
5.5.2	<i>Original Wave Teleoperator With Impedance Matching Elements At Master And Slave</i> <i>104</i>	
5.5.3	<i>Wave Based Teleoperator With Prediction</i>	108
5.5.4	<i>New Wave Variable Teleoperator Architecture</i>	112
5.5.5	<i>New Teleoperator - Asymmetric Delays</i>	118
5.5.6	<i>Performance Comparison - Time Varying Delays</i>	119
5.6	CONCLUSIONS.....	123
CHAPTER 6 : PERFORMANCE ANALYSIS AND IMPROVEMENT OF THE NEW TELEOPERATOR ARCHITECTURE USING THE TEST BED.....		125
6.1	INTRODUCTION	125
6.2	TEST BED RESULTS	125
6.3	FREE SPACE TELEOPERATOR ARCHITECTURE COMPARISON	127

6.3.1	<i>Conventional Bilateral Wave Based Teleoperator Architecture</i>	127
6.3.2	<i>New Wave Variable Teleoperator Architecture</i>	128
6.4	CONTACT WITH A SOLID WALL TELEOPERATOR ARCHITECTURE COMPARISON	129
6.4.1	<i>Conventional Bilateral Wave Based Teleoperator Architecture</i>	129
6.4.2	<i>New Wave Variable Teleoperator Architecture</i>	131
6.5	CONTACT WITH A SOLID WALL AND THEN WALL REMOVED.....	132
6.5.1	<i>Conventional Bilateral Wave Based Teleoperator Architecture</i>	133
6.5.2	<i>New Wave Variable Teleoperator Architecture</i>	135
6.6	NON-LINEAR STICK SLIP ENVIRONMENT	136
6.6.1	<i>Conventional Bilateral Wave Based Teleoperator Architecture</i>	136
6.6.2	<i>New Wave Variable Teleoperator Architecture</i>	138
6.7	CONCLUSIONS.....	139
CHAPTER 7 : CONCLUSIONS AND SUGGESTIONS FOR FUTURE WORK.....		142
7.1	CONCLUSIONS.....	142
7.2	FUTURE WORK – OTHER APPLICATIONS AND DIRECTIONS	146
7.2.1	<i>Shared Control</i>	147
7.2.2	<i>Use Of Direct Force Sensors And Accelerometers</i>	147
7.2.3	<i>Position Outer Loop</i>	148
7.2.4	<i>Peer-to-peer Network</i>	149
7.2.5	<i>Multiple Degrees Of Freedom</i>	151
REFERENCES		152
THESIS PUBLICATIONS.....		160
APPENDIX A : LIST OF SYMBOLS		161
APPENDIX B : EXPERIMENTAL EQUIPMENT DATA		163
B1	TEST BED AC SERVO MOTOR SPECIFICATIONS	163
B2	TEST BED AC SERVO DRIVE SPECIFICATIONS	164
B2	TEST BED 2 FRICTION TEST BED DIRECT DRIVE MOTOR SPECIFICATIONS	165
B3	TEST BED 2 FRICTION TEST BED DIRECT DRIVE DIGITAL AMPLIFIER SPECIFICATIONS	166
B4	TEST BED QUADRATURE ENCODER SPECIFICATIONS	167
B5	TEST BED DATA ACQUISITION CARD SPECIFICATIONS.....	168
APPENDIX C : SIMULINK SYSTEMS USED		169
APPENDIX D : EXPERIMENTAL TEST BED DESIGN AND DRAWINGS.....		172
D1	TEST BED - DRAWING NO. TB01	172
APPENDIX E : SIMPLIFICATION OF TELEOPERATOR EQUATIONS.....		174

E1 ORIGINAL WAVE BASED TELEOPERATOR	174
E2 IMPEDANCE MATCHED TELEOPERATOR AT MASTER AND SLAVE	178
E3 IMPEDANCE MATCHED TELEOPERATOR AT SLAVE ONLY	183
E4 NEW WAVE BASED TELEOPERATOR	187

LIST OF FIGURES

FIGURE 1.1 SAN RAFFAELE HOSPITAL MILAN, ITALY PHOTO COURTESY OF INTUITIVE SURGICAL INC. . .	3
FIGURE 1.1 THE TELEGARDEN, 1995–2004.....	8
FIGURE 1.2 UWA TELEROBOT, 1994–PRESENT	9
FIGURE 1.3 HIGH LEVEL SYSTEM OVERVIEW OF SUPERVISORY TELEOPERATION.....	11
FIGURE 1.4 SUPERVISORY TELEOPERATOR IN CLOSED LOOP REPRESENTATION.....	11
FIGURE 1.5 BILATERAL TELEOPERATOR CONTROL LOOP REPRESENTATION	12
FIGURE 1.6 TELEOPERATOR 2-PORT NETWORK REPRESENTATION	13
FIGURE 1.7 HYBRID REPRESENTATION OF A TELEOPERATOR	14
FIGURE 1.8 WAVE BASED TELEOPERATOR HIGH LEVEL ELEMENTS.....	20
FIGURE 1.9 THE NIEMEYER AND SLOTINE WAVE TELEOPERATOR	21
FIGURE 1.10 POTENTIAL REFLECTION PATHS	25
FIGURE 1.11 PATHS FOR WAVE REFLECTIONS DUE TO IMPEDANCE MISMATCHES	26
FIGURE 1.12 IMPEDANCE MATCHED TELEOPERATOR	28
FIGURE 1.13 VELOCITY CONTROLLED IMPEDANCE MATCHED TELEOPERATOR.....	30
FIGURE 1.14 IMPEDANCE MATCHED TELEOPERATOR AT SLAVE ONLY	31
FIGURE 1.15 BASIC WAVE BASED BILATERAL TELEOPERATOR WITH LOOP SHAPING FILTERS	33
FIGURE 1.16 WAVE BASED BILATERAL TELEOPERATOR WITH SMITH PREDICTION ARCHITECTURE	36
FIGURE 1.17 WAVE BASED BILATERAL TELEOPERATOR WITH TIME FORWARD OBSERVER ARCHITECTURE	37
FIGURE 1.18 WAVE BASED BILATERAL TELEOPERATOR WITH MODE SWITCHING PREDICTION ARCHITECTURE.....	38
FIGURE 1.19 WAVE BASED BILATERAL TELEOPERATOR WITH PREDICTION ARCHITECTURE USING CONTINUOUS ESTIMATION OF SLAVE ENVIRONMENT	39
FIGURE 3.1 LOSSY TRANSMISSION LINE OF LENGTH X.....	49
FIGURE 3.2 LOSSLESS TRANSMISSION LINE OF LENGTH X	49
FIGURE 3.3 WAVE TELEOPERATOR	54
FIGURE 3.4 V_s ONLY RETURNS A FORCE COMPONENT.....	56
FIGURE 3.5 ALTERNATE APPROACH TO CORRECT VELOCITY TRACKING ERRORS.....	57
FIGURE 3.6 EQUIVALENT SIMPLIFIED SYSTEM.....	58
FIGURE 3.7 $\ S(s)\ $ STABILITY RESULTS OF NEW TELEOPERATOR REFLECTION-FREE ARCHITECTURE SYSTEM.....	63
FIGURE 3.8 NEW TELEOPERATOR SYSTEM WITH ASYMMETRIC TIME DELAYS	66
FIGURE 3.9 NEW TELEOPERATOR SYSTEM WITH ASYMMETRIC TIME DELAYS.....	68
FIGURE 3.10 NEW TELEOPERATOR SYSTEM SUITABLE FOR ASYMMETRIC TIME VARYING DELAYS.....	71
FIGURE 4.1 TELEOPERATOR TEST BED	75

FIGURE 4.2 TELEOPERATOR TEST BED AXIS DIRECTIONS	76
FIGURE 4.3 SIMULINK HIGH LEVEL OVERVIEW	77
FIGURE 4.4 HIGH LEVEL INTERFACE OVERVIEW OF TELEOPERATOR TEST BED	78
FIGURE 4.5 LOGICAL LAYOUT OF THE TELEOPERATOR TEST BED.....	79
FIGURE 4.6 ELECTROMECHANICAL BLOCK DIAGRAM.....	80
4.7 HARDWARE VELOCITY RESPONSE TO A STEP TORQUE INPUT.....	81
FIGURE 4.8 REDUCED BLOCK DIAGRAM OF MANIPULATOR	83
FIGURE 4.9 SLAVE MANIPULATOR LOAD TO PROVIDE A CONSISTENT STICK SLIP ENVIRONMENT	84
FIGURE 4.10 HIGH LEVEL INTERFACE OVERVIEW OF TELEOPERATOR TEST BED FORMATTED FOR STICK SLIP FRICTION	85
FIGURE 4.11 LOGICAL LAYOUT OF THE TELEOPERATOR TEST BED FORMATTED FOR STICK SLIP FRICTION	86
4.12 ALTERNATE SLAVE MANIPULATOR HARDWARE VELOCITY RESPONSE TO A STEP TORQUE INPUT ...	87
FIGURE 1.1 SIMPLIFIED SIMULINK MODEL OF TEST BED MANIPULATOR – OPEN LOOP.....	92
FIGURE 1.2 SIMPLIFIED SIMULINK MODEL OF THE CONNECTION SETUP FOR BOTH TEST BEDS	93
FIGURE 1.3 MODEL FOR SIMULATING A SOLID WALL	94
FIGURE 1.4 CLASSICAL FRICTION MODEL STATIC APPROXIMATION	95
FIGURE 1.5 THE KARNOPP FRICTION MODEL	96
FIGURE 1.6 ORIGINAL WAVE BASED TELEOPERATOR	98
FIGURE 1.7 ORIGINAL WAVE-BASED TELEOPERATOR – FREE SPACE DELAY = 200MS (400MS ROUND TRIP)	99
FIGURE 1.8 ORIGINAL WAVE-BASED TELEOPERATOR – FREE SPACE – DELAY = 300MS (600MS ROUND TRIP)	100
FIGURE 1.9 ORIGINAL WAVE-BASED TELEOPERATOR – FREE SPACE – DELAY = 400MS (800MS ROUND TRIP)	101
FIGURE 1.10 ORIGINAL WAVE-BASED TELEOPERATOR — WALL - DELAY = 200MS (400MS ROUND TRIP)	102
FIGURE 1.11 ORIGINAL WAVE-BASED TELEOPERATOR — STICK SLIP - DELAY = 200MS (400MS ROUND TRIP)	103
FIGURE 1.12 ORIGINAL WAVE BASED TELEOPERATOR WITH IMPEDANCE MATCHING AT BOTH MASTER AND SLAVE	104
FIGURE 1.13 IMPEDANCE MATCHED TELEOPERATOR AT MASTER AND SLAVE – FREE SPACE - DELAY = 200MS (400MS ROUND TRIP)	105
FIGURE 1.14 IMPEDANCE MATCHED TELEOPERATOR AT MASTER AND SLAVE – WALL - DELAY = 200MS (400MS ROUND TRIP)	106
FIGURE 1.15 IMPEDANCE MATCHED TELEOPERATOR AT MASTER AND SLAVE — STICK SLIP - DELAY = 200MS (400MS ROUND TRIP)	107
FIGURE 1.16 WAVE BASED BILATERAL TELEOPERATOR WITH SMITH PREDICTION ARCHITECTURE	109
FIGURE 1.17 WAVE BASED TELEOPERATOR WITH PREDICTION - FREE SPACE - DELAY = 200MS (400MS ROUND TRIP).....	110

FIGURE 1.18 WAVE BASED TELEOPERATOR WITH PREDICTION - WALL - DELAY = 200MS (400MS ROUND TRIP)	111
FIGURE 1.19 NEW TELEOPERATOR ARCHITECTURE	112
FIGURE 1.20 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE – FREE SPACE - DELAY = 200MS (400MS ROUND TRIP)	113
FIGURE 1.21 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE – FREE SPACE – DELAY = 300MS (600MS ROUND TRIP)	115
FIGURE 1.22 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE – FREE SPACE – DELAY = 400MS (800MS ROUND TRIP)	115
FIGURE 1.23 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE — WALL - DELAY = 200MS (400MS ROUND TRIP).....	116
FIGURE 1.24 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE – STICK SLIP - DELAY = 200MS (400MS ROUND TRIP).....	117
FIGURE 1.25 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE – FREE SPACE - FORWARD DELAY = 200MS, REVERSE DELAY = 100MS	118
FIGURE 1.26 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE – WALL - FORWARD DELAY = 200MS, REVERSE DELAY = 100MS	119
FIGURE 1.27 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE – FREE SPACE – FAST TIME VARYING DELAY = 100MS - 300MS	120
FIGURE 1.28 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE – WALL – FAST TIME VARYING DELAY = 100MS - 300MS	121
FIGURE 1.29 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE – WALL – SLOW TIME VARYING DELAY = 100MS - 300MS	122
FIGURE 1.30 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE – WALL – SLOW TIME VARYING DELAY = 100MS- 300MS.....	122
FIGURE 6.1 ORIGINAL WAVE-BASED TELEOPERATOR - FREE SPACE.....	127
FIGURE 6.2 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE - FREE SPACE.....	128
FIGURE 6.3 ORIGINAL WAVE-BASED TELEOPERATOR - WALL	129
FIGURE 6.4 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE - WALL	131
FIGURE 6.5 ILLUSTRATES THE HIGH-LEVEL STEPS IN THE SIMULATED NEEDLE PUNCTURE	133
FIGURE 6.6 ORIGINAL WAVE-BASED TELEOPERATOR — REVERSE WALL	134
FIGURE 6.7 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE - REVERSE WALL.....	135
FIGURE 6.8 ORIGINAL WAVE-BASED TELEOPERATOR - STICK SLIP.....	137
FIGURE 6.9 NEW WAVE-BASED TELEOPERATOR ARCHITECTURE - STICK SLIP.....	138
FIGURE 1.1 WAVE BASED BILATERAL TELEOPERATOR WITH AN OUTER POSITION LOOP	148
FIGURE 1.2 POSSIBLE PEER - TO - PEER TELEOPERATOR ARCHITECTURE.....	150
FIGURE 12 WAVE BASED TELEOPERATOR.....	169
FIGURE 13 MASTER WAVE TRANSFORM SUBSYSTEM	170
FIGURE 14 SLAVE WAVE TRANSFORM SUBSYSTEM	170
FIGURE 15 NEW MASTER WAVE TRANSFORM SUBSYSTEM	171

FIGURE 16 NEW SLAVE WAVE TRANSFORM SUBSYSTEM 171

LIST OF TABLES

TABLE 1 COMPARISON OF METHODS.....	45
TABLE 2 COMPARISON OF ELECTRICAL AND MECHANICAL TIME CONSTANTS FOR TEST BED	82
TABLE 3 COMPARISON OF ELECTRICAL AND MECHANICAL TIME CONSTANTS FOR ALTERNATIVE TEST BED	88